APPARATUS AND METHOD FOR TRACE STREAM IDENTIFICATION OF A PROCESSOR RESET

This application claims priority under 35 USC §119(e)(1) of Provisional Application Number 60/434,105 (TI-34663P) filed December 17, 2002.

Related Applications

U.S. Patent Application (Attorney Docket No. TI-34654), entitled APPARATUS AND METHOD FOR SYNCHRONIZATION OF TRACE STREAMS FROM MULTIPLE PROCESSING UNITS, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34655), entitled APPARATUS AND METHOD FOR SEPARATING DETECTION AND ASSERTION OF A TRIGGER EVENT, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the

present application; U.S. Patent Application (Attorney Docket No. TI-34656), entitled APPARATUS AND METHOD FOR STATE SELECTABLE TRACE STREAM GENERATION, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34657), entitled APPARATUS AND METHOD FOR SELECTING PROGRAM HALTS IN AN UNPROTECTED PIPELINE AT NON-INTERRUPTIBLE POINTS IN CODE EXECUTION, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34658), entitled APPARATUS AND METHOD FOR REPORTING PROGRAM HALTS IN AN UNPROTECTED PIPELINE AT NON-INTERRUPTIBLE POINTS IN CODE EXECUTION, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34659), entitled APPARATUS AND METHOD FOR A FLUSH PROCEDURE IN AN INTERRUPTED TRACE STREAM, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34660), entitled APPARATUS AND METHOD FOR CAPTURING AN EVENT OR COMBINATION OF EVENTS RESULTING IN A TRIGGER SIGNAL IN A TARGET PROCESSOR, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34661),

entitled APPARATUS AND METHOD FOR CAPTURING THE PROGRAM COUNTER ADDRESS ASSOCIATED WITH A TRIGGER SIGNAL IN A TARGET PROCESSOR, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34662), entitled APPARATUS AND METHOD DETECTING ADDRESS CHARACTERISTICS FOR USE WITH A TRIGGER GENERATION UNIT IN A TARGET PROCESSOR, invented by Gary L. Swoboda and Jason L. Peck, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent (Attorney Docket No.TI-34664), entitled APPARATUS AND METHOD FOR TRACE STREAM IDENTIFICATION OF A PROCESSOR DEBUG HALT SIGNAL, invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34665), entitled APPARATUS AND METHOD FOR TRACE STREAM IDENTIFICATION OF A PIPELINE FLATTENER PRIMARY CODE FLUSH FOLLOWING INITIATION OF AN INTERRUPT SERVICE ROUTINE; invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34666), entitled APPARATUS AND METHOD FOR TRACE STREAM IDENTIFICATION OF A PIPELINE FLATTENER SECONDARY CODE FLUSH FOLLOWING A RETURN TO PRIMARY CODE EXECUTION, invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent

Application (Docket No. TI-34667), entitled APPARATUS AND METHOD IDENTIFICATION OF A PRIMARY CODE START SYNC POINT FOLLOWING A RETURN TO PRIMARY CODE EXECUTION, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U. S. Patent Application (Attorney Docket No. TI-34668), entitled APPARATUS AND METHOD FOR IDENTIFICATION OF A NEW SECONDARY CODE START POINT FOLLOWING A RETURN FROM A SECONDARY CODE EXECUTION, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34669), entitled APPARATUS AND METHOD FOR TRACE STREAM IDENTIFICATION OF A PAUSE POINT IN A CODE EXECTION SEQUENCE, invented by Gary L. Swoboda, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34670), entitled APPARATUS AND METHOD FOR COMPRESSION OF A TIMING TRACE STREAM, invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application; U.S. Patent Application (Attorney Docket No. TI-34671), entitled APPARATUS AND METHOD FOR TRACE STREAM IDENTIFCATION OF MULTIPLE TARGET PROCESSOR EVENTS, invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application; and U.S. Patent Application (Attorney Docket No. TI-34672), entitled APPARATUS AND METHOD FOR OP CODE EXTENSION IN

PACKET GROUPS TRANSMITTED IN TRACE STREAMS, invented by Gary L. Swoboda and Bryan Thome, filed on even date herewith, and assigned to the assignee of the present application are related applications.

Background of the Invention

1. Field of the Invention

This invention relates generally to the testing of digital signal processing units and, more particularly, to the signals that are transmitted from a target processor to a host processing to permit analysis of the target processing unit operation. Certain events in the target processor must be communicated to the host processing unit along with contextual information. In this manner, the test and debug data can be analyzed and problems in the operation of the target processor identified.

2. Description of the Related Art

As microprocessors and digital signal processors have become increasingly complex, advanced techniques have been developed to test these devices. Dedicated apparatus is available to implement the advanced techniques. Referring to Fig. 1A, a general configuration for the test and debug of a target processor **12** is shown. The test and debug

procedures operate under control of a host processing unit **10**. The host processing unit **10** applies control signals to the emulation unit **11** and receives (test) data signals from the emulation unit **11** by cable connector **14**. The emulation unit **11** applies control signals to and receives (test) signals from the target processing unit **12** by connector cable **15**. The emulation unit **11** can be thought of as an interface unit between the host processing unit **10** and the target processor **12**. The emulation unit **11** processes the control signals from the host processor unit **10** and applies these signals to the target processor **12** in such a manner that the target processor will respond with the appropriate test signals. The test signals from the target processor **12** can be a variety types. Two of the most popular test signal types are the JTAG (Joint Test Action Group) signals and trace signals. The JTAG protocol provides a standardized test procedure in wide use in which the status of selected components is determined in response to control signals from the host processing unit. Trace signals are signals from a multiplicity of selected locations in the target processor **12** during defined period of operation. While the width of the bus **15** interfacing to the host processing unit **10** generally has a standardized dimension, the bus between the emulation unit **11** and the target processor **12** can be increased to accommodate an increasing amount of data needed to verify the operation of the target processing unit **12**. Part of the interface function between

the host processing unit **10** and the target processor **12** is to store the test signals until the signals can be transmitted to the host processing unit **10**.

Referring to Fig. 1B, the operation of the trigger generation unit **19** is shown. The trigger unit provides the main component by which the operation/state of the target processor can be altered. At least one event signal is applied to the trigger generation unit **19**. Based on the identity of the event signal(s) applied to the trigger generation unit **19**, a trigger signal is selected. Certain events and combination of events, referred to as an event front, generate a selected trigger signal that results in certain activity in the target processor such as a debug halt. Combinations of different events generating trigger signals are referred to as jobs. Multiple jobs can have the same trigger signal or combination of trigger signals. In the test and debug of the target processor, the trigger signals can provide impetus for changing state in the target processor or for performing a specified activity. The event front defines the reason for the generation of trigger signal. This information is important in understanding the operation of the target processor because, as pointed out above, several combinations of events can result in the generation of a trigger signal. In order to analyze the operation of the target processing unit, the portion of the code resulting in the trigger

signal must be identified. However, the events in the host processor leading to the generation of event signals can be complicated. Specifically, the characteristics of an instruction at a program counter address can determine whether a trigger signal should be generated. A trigger signal can be an indication of when an address is within a range of addresses, outside of a range of addresses, some combination of address characteristics, and/or the address is aligned with a reference address. In this instance, the address can be the program address of an instruction or a memory address directly or indirectly referenced by a program instruction.

In testing the target processors, certain events must be identified. The reset procedure is a normal system function in which the (target) processor halts the current processing activity and begins a processing activity at preselected program point. However, it is important to determine the point in the original processing procedure where the reset procedure occurs, the duration of the reset procedure, and the starting point of the processing procedure. A reset of a processor can be initiated by the user or, in the processor itself, by identification of a preselected condition.

A need has been felt for apparatus and an associated method having the feature that a reset procedure is identified in

a target processor and occurrence of the reset procedure communicated to the testing apparatus. It is another feature of the apparatus and associated method to transfer information concerning a reset procedure to the testing processing unit using the trace stream. It is a still further feature of the apparatus and associated method to communicate to the testing apparatus when the reset feature is initiated during the program execution. It is yet another feature of the present in invention to communicate to the testing processing unit the duration of the reset procedure.

Summary of the Invention

The aforementioned and other features are accomplished, according to the present invention, by providing the target processor with at least two trace streams. One of the trace streams is a timing trace stream. The second trace stream, when a reset signal resulting from a user input or selected target processor parameters is identified, is provided with a sync marker. The sync marker includes at least one portion identifying the event as a reset procedure, a portion relating the reset procedure to the timing trace stream, and a portion identifying the point in the program execution when the reset procedure is initiated. In addition, the second trace stream includes a sync marker including at least one packet identifying when

the reset procedure is ended. In the preferred embodiment, the second trace stream is a program counter trace stream. The point in the program execution where the reset signal is identified is determined by the program counter address. The time of the occurrence of the reset procedure is determined by trace synchronization markers and by a position of a clock cycle in a timing packet. The end of the reset procedure is marked by a sync marker that includes a header identifying the event as an end of reset and relating the event to the timing trace stream.

Other features and advantages of present invention will be more clearly understood upon reading of the following description and the accompanying drawings and the claims.

Brief Description of the Drawings

Figure 1A is a general block diagram of a system configuration for test and debug of a target processor, while Fig. 1B illustrates the function of the trigger unit.

Figure 2 is a block diagram of selected components in the target processor used the testing of the central processing unit of the target processor according to the present invention.

Figure 3 is a block diagram of selected components of the illustrating the relationship between the components transmitting trace streams in the target processor.

Figure 4A illustrates format by which the timing packets are assembled according to the present invention, while Figure 4B illustrates the inclusion of a periodic sync marker in the timing trace stream according to the present invention.

Figure 5 illustrates the parameters for sync markers in the program counter stream packets according to the present invention.

Figure 6A illustrates the sync markers in the program counter trace stream when a periodic sync point ID is

generated, while Figure 6B illustrates the reconstruction of the target processor operation from the trace streams according to the present invention.

Figure 7A is a block diagram illustrating the apparatus used in reconstructing the processor operation from the trace streams according to the present invention, while Figure 7B is block diagram illustrating where the program counter identification of instructions is provided for the trace streams according to the present invention.

Figure 8A is block diagram of the program counter sync marker generator unit; Figure 8B illustrates the sync markers generated in the presence of a debug halt condition; and Figure 8C illustrates the reconstruction of the processor operation from the trace stream according to the present invention.

Description of the Preferred Embodiment

1. Detailed Description of the Figures

Fig. 1A and Fig. 1B have been described with respect to the related art.

Referring to Fig. 2, a block diagram of selected components of a target processor **20**, according to the present

invention, is shown. The target processor includes at least one central processing unit **200** and a memory unit **208**. The central processing unit **200** and the memory unit **208** are the components being tested. The trace system for testing the central processing unit **200** and the memory unit **202** includes three packet generating units, a data packet generation unit **201**, a program counter packet generation unit **202** and a timing packet generation unit **203**. The data packet generation unit **201** receives VALID signals, READ/WRITE signals and DATA signals from the central processing unit **200**. After placing the signals in packets, the packets are applied to the scheduler/multiplexer unit **204** and forwarded to the test and debug port **205** for transfer to the emulation unit **11**. The program counter packet generation unit **202** receives PROGRAM COUNTER signals, VALID signals, BRANCH signals, and BRANCH TYPE signals from the central processing unit **200** and, after forming these signal into packets, applies the resulting program counter packets to the scheduler/multiplexer **204** for transfer to the test and debug port **205**. The timing packet generation unit **203** receives ADVANCE signals, VALID signals and CLOCK signals from the central processing unit **200** and, after forming these signal into packets, applies the resulting packets to the scheduler/multiplexer unit **204** and the scheduler/multiplexer **204** applies the packets to the test and debug port **205**. Trigger unit **209** receives EVENT signals from the central processing unit **200** and

signals that are applied to the data trace generation unit **201**, the program counter trace generation unit 202, and the timing trace generation unit **203**. The trigger unit **209** applies TRIGGER and CONTROL signals to the central processing unit **200** and applies CONTROL (i.e., STOP and START) signals to the data trace generation unit **201**, the program counter generation unit **202**, and the timing trace generation unit **203**. The sync ID generation unit **207** applies signals to the data trace generation unit **201**, the program counter trace generation unit **202** and the timing trace generation unit **203**. While the test and debug apparatus components are shown as being separate from the central processing unit **201**, it will be clear that an implementation these components can be integrated with the components of the central processing unit **201**.

Referring to Fig. 3, the relationship between selected components in the target processor **20** is illustrated. The data trace generation unit **201** includes a packet assembly unit **2011** and a FIFO (first in/first out) storage unit **2012**, the program counter trace generation unit **202** includes a packet assembly unit **2021** and a FIFO storage unit **2022**, and the timing trace generation unit **203** includes a packet generation unit **2031** and a FIFO storage unit **2032**. As the signals are applied to the packet generators **201**, **202**, and **203**, the signals are assembled into packets of information. The packets in the preferred

embodiment are 10 bits in width. Packets are assembled in the packet assembly units in response to input signals and transferred to the associated FIFO unit. The scheduler/multiplexer **204** generates a signal to a selected trace generation unit and the contents of the associated FIFO storage unit are transferred to the scheduler/multiplexer **204** for transfer to the emulation unit. Also illustrated in Fig. 3 is the sync ID generation unit **207**. The sync ID generation unit **207** applies an SYNC ID signal to the packet assembly unit of each trace generation unit. The periodic signal, a counter signal in the preferred embodiment, is included in a current packet and transferred to the associated FIFO unit. The packet resulting from the SYNC ID signal in each trace is transferred to the emulation unit and then to the host processing unit. In the host processing unit, the same count in each trace stream indicates that the point at which the trace streams are synchronized. In addition, the packet assembly unit **2031** of the timing trace generation unit **203** applies and INDEX signal to the packet assembly unit **2021** of the program counter trace generation unit **202**. The function of the INDEX signal will be described below.

Referring to Fig. 4A, the assembly of timing packets is illustrated. The signals applied to the timing trace generation unit **203** are the CLOCK signals and the ADVANCE signals. The CLOCK signals are system clock signals to

which the operation of the central processing unit **200** is synchronized. The ADVANCE signals indicate an activity such as a pipeline advance or program counter advance (()) or a pipeline non-advance or program counter non-advance (1). An ADVANCE or NON-ADVANCE signal occurs each clock cycle. The timing packet is assembled so that the logic signal indicating ADVANCE or NON-ADVANCE is transmitted at the position of the concurrent CLOCK signal. These combined CLOCK/ADVANCE signals are divided into groups of 8 signals, assembled with two control bits in the packet assembly unit **2031**, and transferred to the FIFO storage unit **2032**.

Referring to Fig. 4B, the trace stream generated by the timing trace generation unit **203** is illustrated. The first (in time) trace packet is generated as before. During the assembly of the second trace packet, a SYYN ID signal is generated during the third clock cycle. In response, the timing packet assembly unit **2031** assembles a packet in response to the SYNC ID signal that includes the sync ID number. The next timing packet is only partially assembled at the time of the SYNC ID signal. In fact, the SYNC ID signal occurs during the third clock cycle of the formation of this timing packet. The timing packet assembly unit **2031** generates a TIMING INDEX 3 signal (for the third packet clock cycle at which the SYNC ID signal occurs) and

transmits this TIMING INDEX 3 signal to the program counter packet assembly unit **2031**.

Referring to Fig. 5, the parameters of a sync marker in the program counter trace stream, according to the present invention is shown. The program counter stream sync markers each have a plurality of packets associated therewith. The packets of each sync marker can transmit a plurality of parameters. A SYNC POINT TYPE parameter defines the event described by the contents of the accompanying packets. A program counter TYPE FAMILY parameter provides a context for the SYNC POINT TYPE parameter and is described by the first two most significant bits of a second header packet. A BRANCH INDEX parameter in all but the final SYNC POINT points to a bit within the next relative branch packet following the SYNC POINT. When the program counter trace stream is disabled, this index points a bit in the previous relative branch packet when the BRANCH INDEX parameter is not a logic "0". In this situation, the branch register will not be complete and will be considered as flushed. When the BRANCH INDEX is a logic "0", this value point to the least significant value of branch register and is the oldest branch in the packet. A SYNC ID parameter matches the SYNC POINT with the corresponding TIMING and/or DATA SYNC POINT which are tagged with the same SYNC ID parameter. A TIMING INDEX parameter is applied relative to a corresponding TIMING

SYNC POINT. For all but LAST POINT SYNC events, the first timing packet after the TIMING PACKET contains timing bits during which the SYNC POINT occurred. When the timing stream is disabled, the TIMING INDEX points to a bit in the timing packet just previous to the TIMING SYNC POINT packet when the TIMING INDEX value is nor zero. In this situation, the timing packet is considered as flushed. A TYPE DATA parameter is defined by each SYNC TYPE. An ABSOLUTE PC VALUE is the program counter address at which the program counter trace stream and the timing information are aligned. An OFFSET COUNT parameter is the program counter offset counter at which the program counter and the timing information are aligned.

Referring to Fig. 6A, a program counter trace stream for a hypothetical program execution is illustrated. In this program example, the execution proceeds without interruption from external events. The program counter trace stream will consist of a first sync point marker 601, a plurality of periodic sync point ID markers 602, and last sync point marker 603 designating the end of the test procedure. The principal parameters of each of the packets are a sync point type, a sync point ID, a timing index, and an absolute PC value. The first and last sync points identify the beginning and the end of the trace stream. The sync ID parameter is the value from the value from the most recent sync point ID generator unit. In the preferred

embodiment, this value in a 3-bit logic sequence. The timing index identifies the status of the clock signals in a packet, i.e., the position in the 8 position timing packet when the event producing the sync signal occurs. And the absolute address of the program counter at the time that the event causing the sync packet is provided. Based on this information, the events in the target processor can be reconstructed by the host processor.

Referring to Fig. 6B, the reconstruction of the program execution from the timing and program counter trace streams is illustrated. The timing trace stream consists of packets of 8 logic "0"s and logic "1"s. The logic "0"s indicate that either the program counter or the pipeline is advanced, while the logic "1"s indicate the either the program counter or the pipeline is stalled during that clock cycle. Because each program counter trace packet has an absolute address parameter, a sync ID, and the timing index in addition to the packet identifying parameter, the program counter addresses can be identified with a particular clock cycle. Similarly, the periodic sync points can be specifically identified with a clock cycle in the timing trace stream. In this illustration, the timing trace stream and the sync ID generating unit are in operation when the program counter trace stream is initiated. The periodic sync point is illustrative of the plurality of periodic sync points that would typically be

available between the first and the last trace point, the periodic sync points permitting the synchronization of the three trace streams for a processing unit.

Referring to Fig. 7A, the general technique for reconstruction of the trace streams is illustrated. The trace streams originate in the target processor **12** as the target processor **12** is executing a program **1201**. The trace signals are applied to the host processing unit **10**. The host processing unit **10** also includes the same program **1201**. Therefore, in the illustrative example of Fig. 6 wherein the program execution proceeds without interruptions or changes, only the first and the final absolute addresses of the program counter are needed. Using the advance/non-advance signals of the timing trace stream, the host processing unit can reconstruct the program as a function of clock cycle. Therefore, without the sync ID packets, only the first and last sync markers are needed for the trace stream. This technique results in reduced information transfer. Fig. 6 includes the presence of periodic sync ID cycles, of which only one is shown. The periodic sync ID packets are important for synchronizing the plurality of trace streams, for selection of a particular portion of the program to analyze, and for restarting a program execution analysis for a situation wherein at least a portion of the data in the trace data stream is lost. The host processor can discard the

(incomplete) trace data information between two sync ID packets and proceed with the analysis of the program outside of the sync timing packets defining the lost data.

As indicated in Fig. 6A, the program counter trace stream includes the absolute address of the program counter for an instruction. Referring to Fig. 7B, each processor includes a processor pipeline **71**. When the instruction leaves the processor pipeline, the instruction is entered in the pipeline flattener **73**. At the same time, an access of memory unit **72** is performed. The results of the memory access of memory unit **72**, which may take several clock cycles, is then merged the associated instruction in the pipeline flattener **73** and withdrawn from the pipeline flattener **73** for appropriate distribution. The pipeline flattener **73** provides a technique for maintaining the order of instructions while providing for the delay of a memory access. In the preferred embodiment, the absolute address used in the program counter trace stream is the derived from the instruction of leaving the pipeline flattener **71**. As a practical matter, the absolute address is delayed. It is not necessary to use a pipeline flattener **73**. The instructions can have appropriate labels associated therewith to eliminate the need for the pipeline flattener **73**.

Referring to Fig. 8A, the major components of the program counter packet generation unit **202** is shown. The program counter packet generation unit **202** includes a decoder unit **2023**, storage unit **2021**, a FIFO unit **2022**, and a gate unit **2024**. PERIODIC SYNC ID signals, TIMING INDEX signals, and ABSOLUTE ADDRESS signals are applied to gate unit **2024**. When the PERIODIC SYNC ID signals are incremented, the decoder unit **2023**, in response to the PERIODIC SYNC ID signal, stores a periodic sync ID header signal group in a predetermined location **2021A** of the header portion of the storage unit **2021**. The PERIODIC SYNC signal causes the gate **2024** to transmit the PERIODIC SYNC ID signals, the TIMING INDEX signals and the ABSOLUTE ADDRESS signals. These transmitted signals are stored in the storage unit **2021** in information packet locations assigned to these parameters. When all of the portions of the periodic sync marker have been assembled in the storage unit **2021**, then the component packets of the periodic sync marker are transferred to the FIFO unit **2022** for eventual transmission to the scheduler/multiplexer unit. Similarly, when a RESET signal is generated and applied to the decoder unit **2023**, the reset header identifying signal group is stored in position **2021A** in the header portion of the storage unit **2021**. The RESET signal applied to decoder unit 2023 results in a control signal being applied to the gate **2024**. As a result of the control signal, the SYNC ID signals, the TIMING INDEX signals, and the ABSOLUTE ADDRESS signals are

stored in the appropriate locations in storage unit **2021**. When the reset signal sync marker has been assembled, i.e., in packets, the sync marker is transferred to the FIFO unit **2022**. When the RESET signal is removed, decoder unit **2023** causes reset-off identifying signals to be stored in the header location **2021A**. The output signal from the decoder unit **2023** As a result of the RESET signal being removed from gate **2023**, a control signal is applied to gate **2024** resulting in the storage of the SYNC ID signals, the TIMING INDEX signals, and the ABSOLUTE ADDRESS signals storage unit **2021** prior to transfer of the sync marker packets to the FIFO unit **2022**. As will be clear, the first (instruction) sync point marker and the last sync point marker are formed in an analogous manner.

Referring to Fig. 8B, examples of the sync markers in the program counter trace stream are shown. The start of the test procedure is shown in first point sync marker 801. Thereafter, periodic sync ID markers 805 can be generated. Other event markers can also be generated. The identification of a RESET signal results in the generation of reset sync marker 810. When the RESET signal is removed, a reset-off sync marker 820 is generated. Between the reset sync marker 810 and the reset-off sync marker 815, one or more periodic sync ID signals can be generated, the number depending on the time interval between the reset sync marker 810 and the reset-off sync marker 815.

Referring to Fig. 8C, the reconstruction of the program counter trace stream from the sync markers of Fig. 8B and the timing trace stream is shown. The first sync point marker indicates the beginning of test procedure with a program counter address of PC. The program continues to execute unit with the program counter addresses being related to a particular processor clock cycle. When the RESET signal is generated, the program counter is at address PC + N+2 and is related to a particular clock cycle. Thereafter, the program counter does not advance as indicated by the logic "1"s associated with each clock cycle. When the RESET signal is removed, the reset-off marker is generated. The program counter is at address PC' and the target processor begins processing at a preselected absolute address.

2. Operation of the Preferred Embodiment

The present invention relies on the ability to relate the timing trace stream and the program counter trace stream. This relationship is provided by having periodic sync ID information transmitted in each trace stream. In addition, the timing packets are grouped in packets of eight signals identifying whether the program counter (or the pipeline address) advanced or didn't advance. The sync markers in the program counter stream include both the periodic sync

ID information and an index indicating the position in the current eight-position timing packet when the event occurred. Thus, the clock cycle of the event can be specified. In addition, the address of the program counter is provided in the program counter sync markers so that the event can be related to the execution of the program. As a result, when a reset sync signal is generated, the location of the signal relative to the target processor clock and to the program execution is established and can be reconstructed. In the preferred embodiment, data (memory access) information is transferred from the target processor to the host processing unit. It is therefore possible to reconstruct the entire operation of the target processor relative to the reset signal from the transmitted trace streams.

The sync marker trace steams illustrated above relate to an idealized operation of the target processor in order to emphasize the features of the present invention. Numerous other sync events (e.g. branch events) will typically be entered in the storage unit and included in the program counter trace stream.

In the foregoing discussion, the sync markers can have additional information embedded therein depending on the implementation of the apparatus generating and interpreting the trace streams. This information will be related to the

parameters shown in Fig. 5. It will also be clear that a data trace stream, as shown in Fig. 2 will typically be present. The periodic sync IDs as well as the timing indexes will also be included in the data trace stream. In addition, the program counter absolute address parameter can be replaced by the program counter off-set register in certain situations.

While the invention has been described with respect to the embodiments set forth above, the invention is not necessarily limited to these embodiments. Accordingly, other embodiments, variations, and improvements not described herein are not necessarily excluded from the scope of the invention, the scope of the invention being defined by the following claims.